

Wireless sensor



Outdoor brightness sensor FAH63

Wireless outdoor brightness sensor, LxWxH = 80x80x30 mm, Protection degree IP54.

The electronic requires no intrinsic power supply, so there is no standby loss.

The wireless outdoor brightness sensor FAH63 powered by a solar module covers the range from 0 to 30 000 Lux. From approx. 300 Lux, it transmits a wireless telegram to the Eltako wireless network every time there is a brightness change of more than approx. 500 Lux within approx. 10 seconds. If the brightness does not change, a control signal is sent approx. every 100 seconds.

New actuators FSR and FSB can cover the range from 0 to approx. 30 Lux using the twilight switch function. A wireless telegram is sent about every 100 seconds within this range.

In as-delivered state the energy accumulators are empty and must therefore be charged in bright daylight for approx. 5 hours.

The power reserve stored in capacitors supplies the power requirement for the night.

In normal ambient brightness (at least a daily average of 200 Lux), the energy of the integrated solar module is sufficient to power the FAH63. The sensor requires no installation depth behind the mounting plate and can be screwed or glued to any flat surface. An adhesive film is supplied.

The complete module can be removed from the frame for screw mounting.

We recommend sheet metal countersink screws 2.9x25 mm, DIN 7982 C, for screw connections. Both with rawl plugs 5x25 mm and with 55 mm switch boxes.

To teach-in in an actuator in teach-in mode, hold the supplied blue magnet or any other magnet at hand below the point on the side panel of the sensor marked by ■. This sends a teach-in telegram.

When teaching-in in actuators, the switching threshold is defined for switching the light on/off depending on the brightness.

Technical data

Protection degree	IP54
Operating temperature	-20 °C / +55 °C