

	<b>MFZ12DDX<sup>b)</sup></b> <b>MFZ12DX<sup>b)</sup></b> <b>RVZ/AVZ/TGI/</b> <b>EAW12DX<sup>b)</sup></b>	<b>MFZ12NP</b>	<b>MFZ12-230 V</b> <b>A2Z12-UC</b>	<b>MFZ61DX<sup>b)</sup></b>	<b>S2U12DDX<sup>b)</sup></b>
<b>Contacts</b>					
Contact material/contact gap	AgSnO <sub>2</sub> / 0.5 mm	AgSnO <sub>2</sub> / 0.5 mm	AgSnO <sub>2</sub> / 0.5 mm	AgSnO <sub>2</sub> / 0.5 mm	AgSnO <sub>2</sub> / 0.5 mm
Spacing of control connections/contact Spacing control connections C1-C2 or A1-A2/contact	6 mm –	3 mm 6 mm	3 mm; A2Z12: 6 mm –	– 6 mm	6 mm –
Test voltage control connections/contact Test voltage C1-C2 or A1-A2/contact	4000V –	2000V 4000V	2000V; A2Z12: 4000V –	2000V 4000V	4000V –
Rated switching capacity	10 A/250 V AC	16 A/250 V AC	10 A/250 V AC	10 A/250 V AC	16 A/250 V AC
Incandescent lamp and halogen lamp load <sup>1)</sup> 230 V	2000 W <sup>3)</sup>	2300 W <sup>3)</sup>	1000 W <sup>3)</sup>	2000 W <sup>3)</sup>	2000 W <sup>3)</sup>
Fluorescent lamp load with KVG* in lead-lag circuit or non compensated	1000 VA <sup>3)</sup>	1000 VA <sup>3)</sup>	500 VA <sup>3)</sup>	1000 VA <sup>3)</sup>	1000 VA <sup>3)</sup>
Fluorescent lamp load with KVG* shunt-compensated or with EVG*	500 VA <sup>3)</sup>	500 VA <sup>3)</sup>	250 VA <sup>3)</sup>	500 VA <sup>3)</sup>	500 VA <sup>3)</sup>
Compact fluorescent lamps with EVG* and energy saving lamps ESL	15x7 W 10x20 W <sup>4)</sup>	15x7 W 10x20 W	1 on ≤ 35A/10ms <sup>2)</sup>	15x7 W 10x20 W <sup>4)</sup>	15x7 W 10x20 W <sup>3) 4)</sup>
Max. switching current DCI: 12V/24 V DC	8 A	–	8 A	8 A	8 A
Life at rated load, cos φ = 1 for incandescent lamps 1000 W at 100/h	> 10 <sup>5</sup>	> 10 <sup>5</sup>	> 10 <sup>5</sup>	> 10 <sup>5</sup>	> 10 <sup>5</sup>
Life at rated load, cos φ = 0.6 at 100/h	> 4 x 10 <sup>4</sup>	> 4 x 10 <sup>4</sup>	> 4 x 10 <sup>4</sup>	> 4 x 10 <sup>4</sup>	> 4 x 10 <sup>4</sup>
Maximum conductor cross-section (3-fold terminal)	6 mm <sup>2</sup> (4 mm <sup>2</sup> )	6 mm <sup>2</sup> (4 mm <sup>2</sup> )	6 mm <sup>2</sup> (4 mm <sup>2</sup> )	4 mm <sup>2</sup>	6 mm <sup>2</sup> (4 mm <sup>2</sup> )
Two conductors of same cross-section (3-fold terminal)	2.5 mm <sup>2</sup> (1.5 mm <sup>2</sup> )	2.5 mm <sup>2</sup> (1.5 mm <sup>2</sup> )	2.5 mm <sup>2</sup> (1.5 mm <sup>2</sup> )	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup> (1.5 mm <sup>2</sup> )
Screw head	slotted / crosshead, pozidriv	slotted / crosshead, pozidriv	slotted / crosshead, pozidriv	slotted / crosshead	slotted / crosshead, pozidriv
Type of enclosure/terminals	IP50 / IP20	IP50 / IP20	IP50 / IP20	IP30 / IP20	IP50 / IP20
<b>Electronics</b>					
Time on	100 %	100 %	100 %	100 %	100 %
Max./min. temperature at mounting location	+50°C/-20°C	+50°C/-20°C	+50°C/-20°C	+50°C/-20°C	+50°C/-20°C
Temperature dependence	< 0.2 % per °C	< 0.2 % per °C	< 0.2 % per °C	< 0.2 % per °C	< 0.2 % je °C
Repeat accuracy at 25°C	±0.1%	±0.1%	±0.1%	±0.1%	±0.1%
Control voltage dependence from 0.9 to 1.1x rated voltage	none	none	none	none	none
Stored energy time in the event of power failure (then total reset)	≥ 0.2 seconds	≥ 0.2 seconds	≥ 0.2 seconds	≥ 0.2 seconds	7 days
Standby loss (active power) 230V	MFZ12DDX: 0.5 W; MFZ12DX: 0.4-0.6 W; RVZ/AVZ/TGI/ EAW12: 0.4 W	0.5 W	0.4 W	0.4 W	0.4 W
Standby loss (active power) 12V/24 V	0.02 W/0.04 W; MFZ12DDX: 0.05 W/0.1 W	–	–	0.02 W/0.04 W	0.03 W/0.06 W
Control current 230 V-control input local ±20%	–	2 mA	2 mA; A2Z12: –	–	–
Control current universal control voltage 8/12/24/230V (<10s) ± 20%	0.05/0.1/0.2/1 mA	2/4/9/5 (100) mA	A2Z12: 0.05/0.1/0.2/1 mA	0.05/0.1/0.2/1 mA	0.04/0.05/0.1/1.2 mA
Max. parallel capacitance (approx. length) of the control leads at 230 V AC	0.2 μF (600 m)	0.01 μF (30 m) C1-C2: 0.03 μF (100 m)	0.01 μF (30 m); A2Z12: 0.2 μF (600 m)	0.2 μF (600 m)	0.2 μF (600 m)

\* EVG = electronic ballast units; KVG = conventional ballast units

<sup>b)</sup> Bistable relay as relay contact. The switched consumer may not be connected to the mains before the short automatic synchronisation after installation has terminated. <sup>1)</sup> For lamps with a load of 150 W max. <sup>2)</sup> A 40-fold inrush current must be calculated for electronic ballast devices. For steady loads of 1200 W or 600 W use the current-limiting relay SBR12 or SBR61. Product group G, page G4. <sup>3)</sup> The maximum load can be used from a delay time or clock cycle of 5 minutes. The maximum load is reduced for shorter times as follows: up to 2 seconds 500 W, up to 2 minutes 1000 W, up to 5 minutes 2000 W.

<sup>4)</sup> When using DX types close attention must be paid that zero passage switching is activated!