


## EUD61M-UC



**Power MOSFET up to 400W. Energy saving lamps ESL up to 100W.  
Standby loss 0.1 watt only. With adjustable minimum brightness.  
With switching operation for children's rooms and snooze function.**

Built-in device for installation. 45 mm long, 55 mm wide, 18 mm deep.

Universal dimmer switch for R, L and C loads up to 400 watt, depending on ventilation conditions. Dimmable energy saving lamps ESL up to 100 watt. Automatic detection of load R+L or R+C. ESL is manually settable.

**Zero passage switching with soft start and soft OFF to protect lamps.**

**Universal control voltage input 8 to 230 V UC**, electrically isolated from the 230V supply voltage and switching voltage.

Short-time control commands switch on/off, permanent control varies the brightness to the maximum level.

An interruption of control changes the direction of dimming.

The brightness level is stored after switching off in case the **function memory** is set. If the **function on max** is set, it always switches on at the maximum brightness level.

In case of a power failure the switching position and the brightness level are stored. If applicable the dimmer will be switched on at the stored brightness level after the supply voltage is recovered.

Automatic electronic overload protection and over-temperature switch-off.

The minimum brightness level (completely dimmed down) can be adjusted with **the upper rotary switch** %⚙️, e.g. for dimmable energy saving lamps.

**The lower function rotary switch** selects 7 different functions.

**Setting of function ESV** same as "memory+soft on" with setting of a release delay up to 90 minutes with the rotary switch %⚙️ if the manual off command is not given. Before time-out switch-off early warning function by dimming down within 1 minute.

**The settings +ESL and -ESL** consider the special conditions regarding dimmable energy saving lamps: The starting operation is optimized and adapted to the dimming curve. In these settings the special switching operation for children's rooms is not possible and no wound (inductive) transformer must be dimmed. In position -ESL Memory is switched off. This can be of advantage for energy saving lamps because cold energy saving lamps require a higher minimum brightness as it will possibly be stored in Memory for warmer energy saving lamps.


**Switching operation for children's rooms:** If the light is switched on by holding down the pushbutton, it starts at the lowest brightness level after approx. 1 second and dims up slowly as long as the pushbutton is held down without modifying the last stored brightness level.

**Snooze function:** With a double impulse the lighting is dimmed down from the current dimming position to the minimum brightness level and switched off. The current dimming position as well as the adjustable minimum brightness level determine the dimming time (max. = 60 minutes) which can be reduced as required. It can be switched off at any time by short-time control commands during the lighting is dimmed down. Holding down the push-button during the dimming down process dims up and stops the snooze function.

Mixing of L loads (inductive loads, e.g. wound transformers) and C loads (capacitive loads, e.g. electronic transformers) is not permitted. R loads (ohmic loads, e.g. 230V incandescent lamps and halogen lamps) may be added anytime.


**Mixing of L loads and C loads** is possible with dimmer switches **EUD12Z** (description page B2) and **EUD12D** (page B3) in connection with capacity enhancer **LUD12** (page B5).

### Function rotary switches



Standard setting ex factory.

### Typical connection



Technical data page B15. Housing for operating instructions GBA12 page Z5.

**EUD61M-UC**

Power MOSFET up to 400W

EAN 4010312107973

**51,80 €/pc.**

Recommended retail prices excluding VAT.