



WIRELESS ACTUATOR IMPULSE SWITCH WITH INTEGR. RELAY FUNCTION FSR61VA-10A



Typical connection



FSR61VA-10A



1 NO contact not potential free 10 A/250 V AC, incandescent lamps up to 2000 watts, off delay with switch-off early warning and switchable pushbutton permanent light. With integrated current measurement up to 10 A. Encrypted wireless, bidirectional wireless and repeater function are switchable. Only 0.8 watt standby loss.

For installation. 45 mm long, 45 mm wide, 33 mm deep. Supply voltage and control voltage 230 V. If a power failure occurs, the switching state is retained. If a power failure occurs repeatedly, the device is switched off in a defined sequence. After installation, wait for short automatic synchronisation before the switched consumer is connected to the mains. Apparent power is measured by the integrated current measurement from approx. 10 VA to 2300 VA when the contact is closed. A wireless telegram is transmitted into the Eltako wireless network within 30 seconds after switching on the load or after a change in power by min 5% and cyclically every 10 minutes.

Evaluation on the computer with Eltako Wireless Building Visualisation and Control Software GFVS. GFVS-Energy supports up to 100 transmitter modules and GFVS 4.0 up to 250 transmitter modules. **You can teach in encrypted sensors.** You can switch on **bidirectional wireless** and/or a **repeater** function. Every change in state and incoming central command telegrams are confirmed by a wireless telegram. This wireless telegram can be taught-in in other actuators, in the GFVS software and in universal displays.

FSR61VA-10A	Wireless actuator Impulse switch with integr. relay function with current measurement	EAN 4010312311462	86,90 €/pc.
-------------	---	-------------------	-------------