



Manuals and documents in further languages:
<https://eltako.com/redirect/FSSA-230V>

FSSA-230V



1 NO contact not potential free 10 A/250 V AC, 230 V LED lamps and ESL up to 400 W, incandescent lamps up to 2000 watts. Encrypted wireless, bidirectional wireless and repeater function are switchable. Only 0.8 watt standby loss.

Adapter for German Socket (Typ F). With increased shock protection.

Supply and switching voltage 230 V.

In case of failure of the supply voltage, the switching state is maintained. The recurrent supply voltage is disconnected in a definite sequence. After plugging wait for short automatic synchronization before the switched consumer is plugged.

This wireless actuator features state-of-the-art hybrid technology that we developed: we combined the wear-free receiver and evaluation electronics and a bistable relay.

You can teach in encrypted sensors.

You can switch on **bidirectional wireless** and/or a **repeater** function.

Every change in state and incoming central command telegrams are then confirmed by a wireless telegram. This wireless telegram can be taught into other actuators, controllers and universal displays.

Up to 35 wireless pushbuttons are assigned **with the left button LRN**, either as a universal pushbutton, direction pushbutton or central pushbutton. For the control of extractor hoods or similar items up to 35 wireless window door contacts FTK or wireless window handle sensors FFG7B can be taught-in. Several FTK or wireless window handle sensors FFG7B are linked together.

If a FTK or wireless window handle sensor FFG7B is taught-in, control commands of eventually taught-in pushbuttons are no longer running.

It can be switched on and off manually **with the right button**.

The LED performs during the teach-in process according to the operation manual. It shows wireless control commands by short flickering during operation.

Technical data page T-3.

FSSA-230V	Wireless actuator Socket switching actuator	Art. No. 30100001	113,80 €/pc.
------------------	--	--------------------------	---------------------