



Wireless sensor

Window/door contact FTKB

Temperature at mounting location:

-20°C up to +50°C.

Storage temperature: -25°C up to +70°C.

Relative humidity:

annual average value <75%.

valid for devices from production week 16/18 (see bottom side of housing)

Wireless window/door contact with battery 75x25x12 mm, pure white.

Starting at 100 Lux daylight the window/door contact FTKB powers itself from a solar cell, otherwise several years with a button cell.

On opening and closing, the related telegram is sent twice in short succession. The current status telegram is sent cyclically every approx. 8 minutes.

Adhesive foil mounting.

Window/door contact dimensions l x w x h:
75 x 25 x 12 mm;
magnet dimensions l x w x h:
37 x 10 x 6 mm.

If the power supply of the solar module is insufficient, the electronics is powered by an internal button cell CR2032 for several years. To change only the housing has to be opened. This is also required to activate the battery supply by pulling out an insulating strip.

When the teach-in button is pressed, the sensor teach-in telegram is sent. When the teach-in button is released, the voltage telegram is sent with the same ID. The current status telegram is sent cyclically every approx. 60 minutes.

For teaching-in into a teachable actuator, the housing has to be opened and the inner button has to be pressed.

After window/door contacts FTK are taught-in in switching actuators FSR14, it is possible to link up to 116 FTKs.

Please refer to the actuator operating

instructions.

When a wireless window/door contact FTK is taught-in in switching actuators FSB14, FSB61NP or FSB71, a lock-out protection is set up while the door is open and disables a Central Down command. Please refer to the actuator operating instructions.

After the window/door contacts FTK are taught-in in switching actuators FHK14, FHK61, FZK14 or FZK61, heating and air-conditioning equipment are switched off when windows are opened.

Both the window/door contact and the magnet have an approx. 10 mm long notch to mark the point where they must be located next to each other when the window is closed. They may not be spaced more than 5 mm apart.

The crossed-out waste container indicates that batteries may not be disposed with other household or commercial waste.



Attention: Danger of explosion if battery is replaced improperly. Only replace it by an equivalent type!

Sensor telegrams (EEP: D5-00-01)
Teach-in telegram DB3..DB0: 0x00, 0x00, 0x00, 0x00
ORG = 0x06Data_byte3 = contact closed = 0x09
Contact open = 0x08Voltage telegram :
(evaluation, e.g. with the GFVS)

ORG = 0x07

Data_byte0 = 0x08

Data_byte1 = 0x00

Battery voltage :

Data_byte2 = 0x00..0xFF equivalent to 0..5V

Energy storage:

Data_byte3 = 0x00..0xFF equivalent to 0..5V

EnOcean wireless

Frequency	868.3 MHz
Transmit power	max. 10 mW

Hereby, Eltako GmbH declares that the radio equipment type FTKB is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address: eltako.com

Must be kept for later use!

Eltako GmbH

D-70736 Fellbach

Technical Support English:

 Michael Thünte +49 176 13582514

 thuente@eltako.de
 Marc Peter +49 173 3180368

 marc.peter@eltako.de
eltako.com