



Bus pushbutton with double rocker



Bus pushbutton with rocker

Typical connections on page 2-12 and 2-13.

B4T65 AND B4FT65



Bus switch 84 x 84 mm external for connection to FTS14TG pushbutton gateway by 2-wire pushbutton bus. Pure white, glossy. Only 0.2 watt standby loss. B4FT65 bus 4-way flat pushbutton in E-design, only 11mm high. B4T65 bus 4-way pushbutton in E-Design, only 16 mm high.

The scope of supply comprises the R1E resp. RF1E frame including snapped-on electronics, a flat rocker and a flat double rocker (all the same colour).

The double rocker permits entry of 4 evaluable signals, but the rocker allows only 2 signals.

At the rear, a 20 cm long red/black by pushbutton bus line is routed externally. Red terminal to BP, black to BN of a pushbutton gateway FTS14TG.

Up to 30 bus switches and/or FTS61BTK pushbutton bus couplers can be connected to terminals BP and BN of an FTS14TG pushbutton gateway.

The permitted maximum line length is 200 m. The RLC device enclosed with the FTS14TG must also be connected to the terminals BP and BN on the bus switch or pushbutton bus coupler furthest away.

A voltage of 29 V DC is supplied to the connected B4 over a 2-wire pushbutton bus which is also used for data transfer.

Please use only conventional bus or telephone lines.

Confirmation telegrams from actuators are displayed by 4 resp. 2 yellow LEDs when the actuator IDs are entered by the PCT14 in the ID table of the FTS14TG.

| | | | |
|--------------------|----------------------------------|-------------------|--------------------|
| B4FT65-wg | Bus flat pushbutton | EAN 4010312315682 | 43,40 €/pc. |
| B4T65-wg | Bus pushbutton in E-Design | EAN 4010312315675 | 42,10 €/pc. |
| RLC element | Range extension for B4T65/B4FT65 | EAN 4010312907092 | 4,00 €/pc. |