


IMPULSE SWITCH WITH INTEGRATED RELAY FUNCTION WITH IP, APPLE HOME VIA WI-FI, 1 NO CONTACT, POTENTIAL FREE 16A, REST-API ESR62PF-IP/110-240V



{REST:API}

Typical connection



ELTAKO Connect-App
<https://eltako.com/redirect/eltako-connect>



Manuals and documents in further languages:
https://eltako.com/redirect/ESR62PF-IP*110-240V

ESR62PF-IP/110-240V



Impulse switch with integrated relay function with IP, Apple Home via Wi-Fi with 1 NO contact, potential free, 16 A/250 V AC, 230 V LED lamps up to 200 W, 230 V incandescent lamps and halogen lamps 2000 W. REST-API. Only 0.7 watt standby loss.

For installation. 49 x 51 mm, 25 mm deep.

The terminals are plug-in terminals for conductor cross-sections of 0.2 mm² to 2.5 mm².

Supply and control voltage locally 110-240 V.

Distance control connections/contact 6 mm.

In case of a power failure the system is disconnected in a preset sequence.

State-of-the-art hybrid technology combines advantages of nonwearing electronic control with high capacity of special relays.

With control input for a mains voltage control button that may be installed in front of it.

Glow lamp current is not permitted.

The Wi-Fi link uses the 2.4 GHz frequency band and permits **Over-the-Air updates (OTA)**.

This actuator is Apple Home certified and can be officially controlled directly via the Apple Home app and Siri. No additional controller or gateway are required:

The **Apple Home app** offers the following functions:

- Create if-then automations including geofencing
- Manual switching
- Call up status

An Apple controller, e.g. HomePod mini, is required for remote access.

As an option, the actuator can be configured via the ELTAKO Connect-App.

A development version of the REST API is available through the device's online product page. This is continuously being further developed.

ESR62PF-IP/110-240V	Impulse switch with integrated relay function with IP, Apple Home via Wi-Fi 1 NO contact, potential free 16 A; REST-API	Art. No. 30062004	58,20 €/pc.
----------------------------	---	--------------------------	--------------------