Tap-radio[®] wireless pushbutton actuator shading TF-TA65J







TF-TA65J Tap-radio® wireless pushbutton actuator shading

Wireless pushbutton actuator shading, 1+1 NO contact $4A/250\,\mathrm{V}$ AC for one shading element motor. For single mounting $84x84x16/33\,\mathrm{mm}$ or mounting into the E-design switching system. Pure white glossy. With integrated universal/direction pushbutton and terminals for additional wired pushbuttons. Power supply 230 V. Only 0.8 watt standby loss. Smart Home sensor and actuator.

Using easy tap-radio® technology, up to 24 wireless universal pushbuttons, wireless direction pushbuttons, wireless central control pushbuttons and motion sensors TF-BSB can be taught in. In addition the actuator can be locally controlled with a conventional 230V wired pushbutton without glow lamp.

The integrated pushbutton works ex work as an universal pushbutton and can be taught-in as an direction pushbutton using the corresponding tap-radio tapping code.

Mounting over a $55\,\mathrm{mm}$ switch box. $16\,\mathrm{mm}$ over and $33\,\mathrm{mm}$ into the box. $230\,\mathrm{V}$ power supply and wired pushbutton terminals on the rear.

