

TECHNICAL DATA

ELECTROMECHANICAL SWITCHING RELAYS AND INSTALLATION CONTACTORS

Type	R12	R81/R91	XR12
Contacts			
Contact material/contact gap	AgSnO ₂ /3 mm	AgSnO ₂ /2 mm	AgSnO ₂ /3 mm ¹⁾
Spacing of control connections/contact	> 6 mm	> 6 mm	> 6 mm
Test voltage contact/contact	2000 V	2000 V	2000 V
Test voltage control connections/contact	4000 V	4000 V	4000 V
Rated switching capacity	16 A/250 V AC 10 A/400 V AC	10 A/250 V AC 6 A/400 V AC	25 A/250 V AC 16 A/400 V AC
230 V LED lamps	up to 200 W ⁵⁾	up to 200 W ⁵⁾	up to 200 W ⁵⁾
Incandescent lamp and halogen lamp load 230 V ²⁾	2300 W	2300 W	2300 W
Fluorescent lamp load with KVG* in lead-lag circuit or non compensated	2300 VA	2300 VA	3600 VA
Fluorescent lamp load with KVG* shunt-compensated or with EVG*	500 VA	500 VA	1000 VA
Compact fluorescent lamps with EVG* and energy saving lamps ESL	I on ≤ 140 A/10 ms ³⁾	I on ≤ 70 A/10 ms ³⁾	I on ≤ 140 A/10 ms ³⁾
HQL and HQL non compensated	500 W	-	500 W
Max. switching current DC1: 12 V/24 V DC	8 A	8 A	12 A
Life at rated load, cos φ = 1 or incandescent lamps 1000 W at 100/h	> 10 ⁵	> 10 ⁵	> 10 ⁵
Life at rated load, cos φ = 0.6 at 100/h	> 4x10 ⁴	> 4x10 ⁴	> 4x10 ⁴
Max. operating cycles	10 ³ /h	10 ³ /h	10 ³ /h
Closing time	10-20 ms	10-20 ms	10-20 ms
Opening time	5-15 ms	5-15 ms	5-15 ms
Switch position indication	yes	yes	yes
Manual control	yes	yes	yes
Maximum conductor cross-section	6 mm ²	4 mm ²	6 mm ²
Two conductors of same cross-section	2.5 mm ²	1.5 mm ²	2.5 mm ²
Screw head	slotted/crosshead, pozidriv	slotted/crosshead, pozidriv	slotted/crosshead, pozidriv
Type of enclosure/terminals	IP50/IP20	IP50/IP20	IP50/IP20
Solenoid System			
Time on	100% ⁴⁾	100%	100% ⁴⁾
Max./min. temperature at mounting location	+50°C/-5°C	+50°C/-5°C	+50°C/-5°C
Control voltage range	0.9 to 1.1 x rated voltage	0.9 bis 1,1 x rated voltage	0.9 to 1.1 x rated voltage
Coil power loss AC+DC ±20%	1- and 2-pole: 1.9 W 4-pole: 4 W	R81: 5 W R91: 2,5 W	1- and 2-pole: 1,9 W 4-pole: 4 W
Total power loss with continuous excitation at rated voltage and rated contact load	1-pole: 4 W, 2-pole: 6 W 4-pole: 12 W	1-pole: 7 W 2-pole: 9 W	1-pole: 4 W, 2-pole: 6 W 4-pole: 12 W
Max. parallel capacitance (length) of control lead	0.06 μF (ca. 200 m)	0.06 μF (ca. 200 m)	0.06 μF (ca. 200 m)
Max. voltage induced at the control inputs	0.2 x rated voltage	0.2 x rated voltage	0.2 x rated voltage

* EVG = electronic ballast units; KVG = conventional ballast units.

¹⁾ Contact distance of the NC contacts 1.2mm.

²⁾ Contact spacing of NC contacts 1.2 mm.

³⁾ A 40-fold inrush current must be calculated for electronic ballast devices. For steady loads of 1200 W or 600 W use the current-limiting relay SBR12 or SBR61. See chapter 14, page 14-8.

⁴⁾ Whenever several impulse switches are continuously energised make sure there is adequate ventilation as a function of the calculated power loss.

⁵⁾ Due to different lamp electronics and depending on the manufacturer, the maximum number of lamps may be limited, especially if the wattage of the individual lamps is very low (e.g. with 2 W LEDs).

To comply with DIN VDE 0100-443 and DIN VDE 0100-534, a Type 1 or Type 2 surge protection device (SPD) must be installed.