

3 CHANNELS DALI LED DIMMER 8 A DL-3CH-8A-DC12+



DL-3CH-8A-DC12+

NEW

3 channels DALI LED dimmer for luminary installation and flush-mounted box. 59x33x15 mm.  
Protection class IP20. Only 0.12 watt standby loss.

Designed to control **constant voltage** LED modules (CV) at operating voltages of 12 V to 48 V, operating mode DT6: separate control of channels via 3 DALI addresses.  
Operating mode Colour&Dim: activated by 2 DALI addresses, one to adjust brightness and one to set the colour.  
SwitchDim2: operation via 2 pushbutton inputs permits control of brightness and colour without DALI.  
Dimming range 0.1%-100%.  
Switchable PWM frequency (122 Hz/244 Hz/488 Hz/976 Hz).  
Power supply from 12 V to 48 V DC (depending on operating voltage of LED modules).  
Connected current 8 A. The maximum connected current can be distributed to any channel.  
High efficiency.  
Configuration via DALI Cockpit PC software and DALI USB interface.

Operating modes:

The device has several operating modes:  
**DT6** (as-delivered state): In this operating mode each channel is controlled by a separate DALI address (Device Type 6). Alternatively, operation can also take place by two pushbutton inputs (SwitchDim2): SwD1: brightness. Press pushbutton briefly: On/Off. Press pushbutton long: Dim.  
SwD2: Scene switch (press pushbutton briefly).  
**Colour&Dim**: This operating mode is used to control RGB luminaries. Control is by means of 2 DALI addresses; one address affects brightness and the other affects channel distribution (e.g.: colour). Colour&Dim mode is used to adjust colour temperature without affecting brightness and vice versa. Adjustment is by means of DALI standard commands such as Dim Up/Down. This permits all customary controls and gateways (e.g. KNX). This control option is an alternative to DT8-RGBWAF mode.  
Operable via DALI or SwitchDim2: DALI address 1, SwD1: brightness. DALI address 2, SwD2: Colour.

DL-3CH-8A-DC12+	3 channels DALI LED dimmer 8 A	EAN 4010312321546	99,20 €/pc.
-----------------	--------------------------------	-------------------	-------------