

FPLT14



Wireless Powerline tunnel gateway. Uni- and bidirectional. Standby loss only 0.4 watt.

Modular device for DIN-EN 60715 TH35 rail mounting.

2 module = 36 mm wide, 58 mm deep.

Supply voltage 230 V.

Connection to the ELTAKO RS485 bus. Bus cross wiring and power supply with jumper.


This gateway transmits RS485 bus telegrams over powerline with large distance over the electrical net. Minimum 2 pcs FPLT14 are required.

Up to 10 FPLT14 can unidirectionally send the bus telegrams of their FAM14 / FTS14KS installation with Powerline to another FAM14 / FTS14KS installation via a local FPLT14.

Teach-in up to 120 telegram IDs according to the operating instructions, also with PCT14.

Two FPLT14 can exchange the bus telegrams bidirectionally from 2 FAM14 / FTS14KS installations with Powerline via the installed wires. Teach-in up to 120 telegram IDs according to the operating instructions, also with PCT14. Because of the transmission delay, short-click evaluations for FUD and FSB actuators are not possible.

Function rotary switches



Standard setting ex works.



Manuals and documents in further languages:
<https://eltako.com/redirect/FPLT14>

FPLT14	Wireless Powerline tunnel gateway	Art. No. 30014078	100,00 €/pc.
--------	-----------------------------------	-------------------	--------------