

THE HOME OF INNOVATION.

Eltako

DO SWITCHING DEVICES GIVE UP THE GHOST AFTER CONVERSIONS TO LED LAMPS?


LED lamps are a welcome alternative to energy-saving bulbs, especially as a retrofit variant. But the downside is that not every incandescent bulb can be simply replaced by a retrofitted LED lamp. In most cases, the high inrush current of LEDs can lead to massive disturbances in the electrical installation – it may even cause contact wear or trigger circuit breakers.

The coupling relay KRW12DX-UC with a 500 A/2 ms tungsten pre-contact is switched downstream of the switching device to attenuate high inrush currents. This reduces wear on the switching device contacts and prolongs the service life of the lamps and the entire electrical installation.



KRW12DX-UC

ELECTRONIC COUPLING RELAY KRW12DX-UC



KRW12DX-UC



1 NO contact potential free 16 A/250 V AC with tungsten pre-contact. The pre-run contact closes before the main contact and thus handles inrush current from LED lamps that occurs over a few ms. Max. inrush current 500 A/2 ms. 230 V LED lamps up to 600 W, incandescent lamp load 3300 W. No standby loss.

Modular device for DIN-EN 60715 TH35 rail mounting. 1 module = 18 mm wide, 58 mm deep. State-of-the-art hybrid technology combines advantages of nonwearing electronic control with high capacity of special relays.

With the patented ELTAKO Duplex technology (DX) the normally potential-free contacts can still switch in zero passage when switching 230 V AC 50 Hz and therefore drastically reduce wear. Simply connect the neutral conductor to the terminal (N) and L to 1(L) for this. This gives an standby consumption of only 0.1 watt.

If the contact is used for controlling switching devices which do not perform zero passage switching themselves, (N) should not be connected because the additional closing delay otherwise causes the opposite effect.

Universal control voltage 12 to 230 V UC.

Low switching noise.

Contact position indicator with LED.


By using a bistable relay coil power loss and heating is avoided even in the on mode.

The relay contact can be open or closed when putting into operation. It will be synchronised at first operation.

This relay is not suitable to feed back the switching voltage signal of a dimmer switch.

Use only relays ESR12DDX-UC, ESR12NP-230V+UC or ESR61NP-230V+UC for this purpose.

Typical connection



ES12Z with KRW12DX-UC

If N is connected, the zero passage switching is active.



Manuals and documents in further languages:
<https://eltako.com/redirect/KRW12DX-UC>

KRW12DX-UC	Coupling relay, 1 NO contact 16 A	Art. No. 22100800	55,00 €/pc.
------------	-----------------------------------	-------------------	-------------

**SALES MANAGER UK
STEPHEN PAYNE**

+ 44 7810 094 384
stephen.payne@eltako.com

Eltako