

Electronical single-phase energy meters and three-phase energy meters for meter mounting installation



The smart counting champions

Single-phase energy meter 60A WSZ60

with drum type register and
MID approval



Three-phase energy meter 3x60A DSZ60

with drum type register and
MID approval



Three-phase energy meter 3x60A DSZ60D

with display and MID approval



- with MID approval
- follow-up models of the phase-out Ferraris meters with and without PTB
- 3-point energy meter mounting

Single-phase energy meter WSZ60

Three-phase energy meter DSZ60 and DSZ60D, MID approval

WSZ60

MID



Maximum current 60A, standby loss 1.2 watt.

Single-phase energy meter for 3-point energy meter mounting.

Accuracy class B.

This single-phase energy meter measures active energy by means of the current between input and output. The internal power consumption of 1.2 watt active power is neither metered nor indicated.

1 phase conductor with a max. current up to 60A can be connected. The inrush current is 10mA. The meter can be read anytime without power supply.

Power consumption is shown by a red LED flashing at a rate of 1000 times per kWh. Permanent light: halt; light off: free of tension.

WSZ60

MID approval

EAN 4010312501368

50,30 €/pc.

DSZ60

MID



Maximum current 3x60A, standby loss 1 watt per path.

Three-phase energy meter for 3-point energy meter mounting.

Accuracy class B.

This directly measuring three-phase energy meter measures active energy by means of the current between input and output. The internal power consumption of 1 watt active power per path is neither metered nor indicated.

1, 2 or 3 phase conductors with max. currents up to 60A can be connected.

The inrush current is 10mA. The meter can be read anytime without power supply.

The N terminal must always be connected.

Power consumption is shown by a red LED flashing at a rate of 500 times per kWh. Permanent light: halt; light off: free of tension.

DSZ60

MID approval

EAN 4010312501351

97,40 €/pc.

DSZ60D

MID



Maximum current 3x60A, standby loss 1 watt per path.

Three-phase energy meter for 3-point energy meter mounting.

Accuracy class B.

With additional terminals to switch over to a second tariff.

This directly measuring three-phase energy meter measures active energy by means of the current between input and output. The internal power consumption of 1 watt active power per path is neither metered nor indicated.

1, 2 or 3 phase conductors with max. currents up to 60A can be connected.

The inrush current is 10mA.

The N terminal must always be connected.

The 7 segment LC display is also legible without external power supply.

Power consumption is shown by a red LED flashing at a rate of 500 times per kWh. Permanent light: halt; light off: free of tension.

DSZ60D

MID approval

EAN 4010312501344

119,30 €/pc.

Recommended retail prices excluding VAT.

	WSZ60	DSZ60	DSZ60D
Rated voltage Extended range	230 V, 50Hz -10 % / +10 %	3x230/400V, 50Hz -10 % / +10 %	3x230/400V, 50Hz -10 % / +10 %
Reference current I_{ref} (Limiting current I_{max})	5 (60) A	3x5 (60) A	
Internal consumption Active power	1.2 W	1 W per path	1 W per path
Display active power	drum type register with 7 digits and 1 decimal digit		LC display 7 digits, therefrom 1 decimal digit
Accuracy class $\pm 1\%$	B	B	B
Backstop	yes	yes	yes
Inrush current	10 mA	10 mA	10 mA
Number of tariffs	1	1	2
Operating temperature	-40/+70°C		-25/+70°C
Protection degree	IP51	IP51	IP51
Maximum conductor cross section	35 mm ²	35 mm ²	35 mm ²
weight	1.3 kg	1.7 kg	1.6 kg
dimensions	176x121x63 mm	270x178x60mm	
EG model test certificate	DE-07-MI003-PTB 015	DE-08-MI003-PTB 013	

Fellbach

Eltako Headquarter
Hofener Straße 54
70736 Fellbach
☎ 0711 94350000
☎ 0711 5183740
✉ info@eltako.de
✉ kundenservice@eltako.de

Baden-Württemberg

Carsten Krampe
75172 Pforzheim
☎ 0173 3180392
✉ krampe@eltako.de

Bavaria (North)

Horst Rock
91126 Schwabach
☎ 09122 61179
☎ 09122 61159
✉ rock@eltako.de

Bavaria (South)

Elka Hugo Kruschke GmbH
82024 Taufkirchen
☎ 089 3090409-0
☎ 089 3090409-50
✉ kruschke@eltako.de

Berlin/Brandenburg/ Saxony (East)

Olaf Knobel
15746 Groß-Köris
☎ 033766 21240
☎ 033766 21241
☎ 0176 13582503
✉ knobel@eltako.de

Hamburg/Schl.-Holstein/Bremen

Gunnar Wetteborn
25355 Barmstedt
☎ 0176 13582502
☎ 04123 6834673
✉ wetteborn@eltako.de

Hessen

Daniel Böth
63811 Stockstadt am Main
☎ 0173 3180391
✉ boeth@eltako.de

Mecklenburg-Vorpommern/ Brandenburg (North)/ Saxony-Anhalt (North)

Klaus-Peter Schmitz
18276 Sarnstorf
☎ 03843 215884
☎ 03843 215884
☎ 0176 13582501
✉ schmitz@eltako.de

Lower Saxony

Detlef Hilker
31840 Hessisch Oldendorf/Barksen
☎ 05152 6984480
☎ 0173 3180390
✉ hilker@eltako.de

North Rhine-Westphalia (East)

Kay Westphal
44265 Dortmund
☎ 0176 13582506
☎ 0231 734171
✉ westphal@eltako.de

North Rhine-Westphalia (West)

Paul Frieg
46395 Bocholt
☎ 0176 13582507
☎ 02871 310988
✉ frieg@eltako.de

Rhineland-Palatinate/Saarland

Rainer Brilmayer
55411 Bingen
☎ 0176 13582516
✉ brilmayer@eltako.de

Thuringia/Saxony (West)/ Saxony-Anhalt (South)

Andreas Misch
39218 Schönebeck OT Elbenau
☎ 0176 13582505
✉ misch@eltako.de

Austria (West)

Representative Robert Goedicke
☎ +43 664 1823322
✉ goedicke@eltako.com

Austria (East)

Representative Andreas Kaider
☎ +43 699 11090025
✉ kaider@eltako.com

Belgium/France/ Luxembourg

Serelec n.v.
B-9000 Gent
☎ +32 9 2234953
✉ info@serelec-nv.be

Cyprus

MeshMade Ltd
CY 1096, Nicosia
☎ +357 7000 6374
✉ info@meshmade.com

Czech Republic

Representative Peter Loužecký
CZ-40011 Ústí nad Labem
☎ +420 475 621132
☎ +420 724 175676
✉ louzECKY@eltako.com

Denmark

SOLAR A/S
DK-6600 Vejle
☎ +45 76 961200
✉ jni@solar.dk

Gulf area

M/S Golden Sand Trading
U.A.E. – Dubai
☎ +9 71 43595611
✉ vasu2000@emirates.net.ae

Iceland

Reykjafell Ltd.
IS-125 Reykjavik Iceland
☎ +35 4 5886010
✉ reykjafell@reykjafell.is

Israel

Avital B.S. Ltd
Il-Holon
☎ +97 23 5587717
✉ avitalbs@zahav.net.il

Italy

Representative Tommaso Scrofani
I-64025 Pineto TE
☎ +39 085 9491796
☎ +39 347 3774888
✉ scrofani@eltako.com

Norway

Malthe Winje Automasjon AS
NO-1415 Oppegard
☎ +47 66996100
✉ firmapost@mwa.no

Netherlands (North)

Representative Hans Oving
NL-7701 VV Dedemsvaart
☎ +31 523 616688
☎ +31 6 21816115
✉ oving@eltako.com

Netherlands (South)

Representative Dennis Schellenberg
NL-5854 PC Bergen (LB)
☎ +31 6 50419067
✉ schellenberg@eltako.com

Portugal

TEV2 – Dist. Mat. Eléctrico, Lda
P-4470-434 Maia
☎ +351 229 478 170
✉ info@tev.pt

Russia

ATLAS Group JSC
RU-127591 Moscow
☎ +7 495 6423463
✉ eltako@atlasgroup.ru

Sweden (North/Middle)

Representative Patrick Savinainen
S-69332 Degerfors
☎ +46 070 9596906
✉ patrick@eltako.com

Sweden (West/East)

Representative Dan Koril
S-57010 Korsberga
☎ +46 070 3201102
✉ dan@eltako.com

Sweden (South)

Representative Jonas Lundquist
S-26433 Klippan
☎ +46 073 5815692
✉ jonas@eltako.com

Switzerland

Demelectric AG
CH-8954 Geroldswil
☎ +41 43 4554400
✉ info@demelectric.ch

Spain

Representative Thomas Klassmann
E-08397 PINEDA/Poble Nou
☎ +34 93 7692419
☎ +34 650 959702
✉ klassmann@eltako.com

South Africa

Innomatic (Pty) Ltd - Franz Markt
ZA-Midrand
☎ +27 11 8400840
✉ sales@innomatic.co.za

Technical support:

☎ +49 176 13582514 ✉ thuenta@eltako.de
☎ +49 711 94350002 ✉ technik-beratung1@eltako.de

Export Sales Manager:

☎ +49 711 94350005 ✉ export@eltako.de



Eltako GmbH

Hofener Straße 54, D-70736 Fellbach

☎ +49 711 94350000 ☎ +49 711 5183740

✉ info@eltako.de 🌐 www.eltako.de