



Manuals and documents in further languages:  
<http://eltako.com/redirect/BPS55-L62>

## BPS55-L62



**Blisterpack switching with wireless pushbutton F2T55E-wg and wireless light actuator FL62-230V. Smart Home sensor and Smart Home actuator.**

**F2T55E-wg:** Wireless 2-way pushbutton in E-Design55, 80 x 80 mm external dimensions, internal frame dimensions 55 x 55 mm, 15 mm high. Generates the power for wireless telegrams itself when the button is pressed, therefore there is no connecting wire and no standby loss. With rocker. Smart Home sensor. Wireless pushbuttons with one rocker can transmit two evaluable signals: press rocker up and press rocker down. The mounting plate can be screwed over a flush-mounting box with a screw spacing of 60 mm or screwed on a flat surface. The wireless pushbutton can be glued to the wall, on glass or on furniture using the enclosed adhesive foil.

**FL62-230V:** Wireless light actuator 10 A/250 V AC. Impulse switch with NO contact, potential free. 230 V LED lamps and ESL up to 200 W. 230 V incandescent lamps and halogen lamps 1000 W. For installation. 49 x 51 mm wide, 20 mm deep. Standby loss only 0.4 watt. **The terminals are plug-in terminals for conductor cross-sections of 0.2 mm<sup>2</sup> to 2.5 mm<sup>2</sup>.** The convenient tap technology permits the teach-in of up to 32 wireless universal pushbuttons, wireless direction pushbuttons, wireless central control pushbuttons and motion sensors. Bidirectional wireless switchable. **Distance between control terminals and contact 6 mm.** Supply voltage, switching voltage and control voltage local 230 V. If supply voltage fails, the device is switched off in defined mode. When the supply voltage is restored, the device is switched off in a defined process. After installation, wait for the short automatic synchronisation before connecting the switched user to the network. In addition to the wireless control input via an internal antenna, this wireless actuator can also be controlled locally by a conventional 230 V control switch if fitted previously. Glow lamp current is not permitted.

BPS55-L62	Blisterpack switching	Art. No. 30001065	119,70 €/pc.
-----------	-----------------------	-------------------	--------------