



WEEE registration number DE 30298319



Manuals and documents in further languages:
<https://eltako.com/redirect/FASWZ-16A>

FASWZ-16A



Wireless outdoor socket energy meter, maximum current 16 A. 116x56x46 mm (measurements without plug), black. Suitable for both indoors and outdoors, IP44 (splash-proof). Only 0.4 watt standby loss. Smart Home actuator.

Adapter for German Socket (Type F). With increased shock protection.

This single-phase energy meter measures active energy by means of the current between input and output and transmits the consumption and meter reading over the ELTAKO wireless network.

Accuracy class B (1%).

Evaluation and smart connection via a controller.

The internal power consumption of max. 0.4 watt active power is not metered.

The inrush current is 20 mA.

The consumption is saved to a non-volatile memory and is immediately available again after a power failure.

Wireless telegrams: A telegram is transmitted within 30 seconds if the power status changes by min. 10 percent. A change in meter reading is transmitted immediately.

A full telegram comprising meter reading and power status is transmitted every 10 minutes.

After plugging in the counter and also when pressing the *LRN* button, a **learn telegram**, a counter reading telegram and a power telegram are sent.

FASWZ-16A	Wireless outdoor socket energy meter	Art. No. 30100015	114,90 €/pc.
-----------	--------------------------------------	-------------------	--------------