

## WIRELESS PUSHBUTTON ACTUATOR DIMMING WITHOUT N CONNECTION IN E-DESIGN55 FTA55DL-wg





## FTA55DL-wg

Wireless pushbutton actuator dimming without N connection. For single mounting  $80 \times 80 \times 15/33$  mm or mounting into the E-design55 switching system. Pure white glossy. With Power MOSFET. 230 V incandescent lamps and halogen lamps up to 200 W, depending on ventilation conditions. Dimmable energy saving lamps ESL and 230V LED lamps in 'trailing edge' mode up to 200 W or up to 40 W in 'leading edge' mode, depending on ventilation conditions. Min. load 20 W at 'trailing edge' mode and 8 W at 'leading edge' mode. No inductive (wound) transformers. With switching operation for children's rooms and snooze function. With integrated universal/direction pushbutton and terminals for additional wired pushbuttons. Supply voltage 230 V. Only 0.7 watt standby loss. Smart Home sensor and actuator.

FTA55DL-wg	Wireless pushbutton actuator dimmer without N	No longer available
	connection, pure white glossy	