Tap-radio[®] wireless pushbutton actuator shading TF-TA55J







TF-TA55J Tap-radio® wireless pushbutton actuator shading

Wireless pushbutton actuator shading, 1+1 NO contact 4A/250V AC for one shading element motor. For single mounting 80x80x15/33 mm or mounting in the 55 mm switch system. Pure white glossy. With integrated universal/direction pushbutton and terminals for additional wired pushbuttons. Power supply 230 V. Only 0.8 watt standby loss. Smart Home sensor and actuator.

Using easy tap-radio® technology, up to 24 wireless universal pushbuttons, wireless direction pushbuttons, wireless central control pushbuttons and motion sensors TF-BSB can be taught in. In addition the actuator can be locally controlled with a conventional 230V wired pushbutton without glow lamp.

The integrated pushbutton works ex work as an universal pushbutton and can be taught-in as an direction pushbutton using the corresponding tap-radio tapping code.

Mounting over a $55\,\mathrm{mm}$ switch box. $15\,\mathrm{mm}$ over and $33\,\mathrm{mm}$ into the box. $230\,\mathrm{V}$ power supply and wired pushbutton terminals on the rear.

